

## Saving / Loading

|             |                                    |
|-------------|------------------------------------|
| Reset Desk  | SETUP / CLEAR OPTIONS / RESET DESK |
| Save Show   | SETUP / FILES / SAVE SHOW          |
| Load Show   | SETUP / FILES / LOAD SHOW          |
| Leave Setup | SETUP                              |

## Monitor Windows

|                   |  |
|-------------------|--|
| Output Window     | OUTPUT                                 |
| Program Window    | PGM WIN                                |
| Memories Window   | MEMORIES                               |
| Submasters Window | SUBMASTER                              |
| Palette Windows   | SHIFT + COLOUR / SHIFT + BEAMSHAPE etc |
| Macro Window      | SHIFT + MACRO                          |
| Group Window      | SHIFT + GROUPS                         |
| Help              | SHIFT + LEFT + RIGHT                   |
| Resize Window     | SPECIAL / PAGE 1 / SIZE                |
| Close Window      | SPECIAL / PAGE 1 / CLOSE               |
| Select Window     | SPECIAL / PAGE 1 / SELECT              |

## Dimmer Control

|                             |   |
|-----------------------------|---|
| Turn channel on             | <Push the fader up>                     |
| Flash a channel             | <Press the flash button>                |
| Change flash mode           | SPECIAL / FLASH MODE / <select on MFKs> |
| Clear the program window    | CLEAR                                   |
| Clear the selected fixtures | CLEAR CLEAR                             |
| Command Line mode           | SPECIAL / PAGE 2 / SHOW COMMAND LINE    |

## Fixture Control

|                    |   |
|--------------------|---|
| Select Fixture     | FIXTURES / <select on MFKs>                             |
| Home Fixture       | HOME  |
| Dimmer control     | POSITION / <3 <sup>rd</sup> wheel>                      |
| Position control   | POSITION / <wheels>                                     |
| Colour control     | COLOUR / <wheels>                                       |
| Beamshape control  | BEAMSHAPE / <wheels>                                    |
| Home just Position | POSITION + HOME (also COLOUR + HOME, etc)               |
| Untag an attribute | CLEAR + COLOUR  |
| Untag a parameter  | CLEAR + <move wheel>                                    |
| Fan a parameter    | SHIFT + <move wheel>                                    |
| Change Fan mode    | SETUP + COLOUR / <Shifted Wheel Mode> / <select> / <OK> |

## Palettes

|                         |  |
|-------------------------|--|
| Create Auto Palettes    | SETUP / PATCH / AUTO MENUS / CREATE AUTO PALETTES                                      |
| Access a colour palette | FIXTURES / <select on MFKs> / COLOUR / <select on MFKs>                                |
| Store a colour palette  | <setup fixtures as required> / COLOUR / <hold down MFK>                                |
| Name a Colour Palette   | NAME / COLOUR / <select number field and enter number> / <arrow down> / <name> / ENTER |

## Groups

|                    |   |
|--------------------|---|
| Create Auto Groups | SETUP / PATCH / AUTO MENUS / CREATE AUTO GROUPS                     |
| Select a Group     | GROUPS / <select on MFKs>   |
| Store a Group      | <setup fixtures as required> / GROUPS / <hold down MFK>             |
| Name a GROUP       | NAME / GROUPS / <select field> / <no> <arrow down> / <name> / ENTER |

## Patching

|                    |   |
|--------------------|---|
| Add Fixture        | SETUP / PATCH / ADD FIXTURES / <follow wizard>              |
| Edit Fixture Patch | SETUP / PATCH / EDIT FIXTURES / <select fixtures> / <PATCH> |
| Delete Fixture     | SETUP / PATCH / EDIT FIXTURES / <select fixtures> / <PATCH> |

## Memories

|                   |   |
|-------------------|---|
| Record a Memory   | MEMORIES / <select using arrow keys> / RECORD                       |
| Playback a Memory | MEMORIES / <select using arrow keys> / GO                           |
| Delete a Memory   | MEMORIES / <select using arrow keys> / DELETE / OK                  |
| Name a Memory     | MEMORIES / <select using arrow keys> / NAME / <name> / ENTER        |
| Set Fade Times    | MEMORIES / <select using arrow keys> / TIME / <control with wheels> |
| Release Memories  | CLEAR + MEMORIES  |

## Submasters

|                            |  |
|----------------------------|--|
| Record a Submasters        | SUBMASTERS / <select using flash buttons> / RECORD                       |
| Playback a Submaster       | <Use the fader>  |
| Delete a Submaster         | SUBMASTERS / <select using flash buttons> / DELETE / OK                  |
| Name a Submaster           | SUBMASTERS / <select using flash buttons> / NAME / <name> / ENTER        |
| Set Fade Times             | SUBMASTERS / <select using flash buttons> / TIME / <control with wheels> |
| Create Range Submaster     | SHIFT + COPY / <popup window> / ENTER                                    |
| Release all Submasters     | CLEAR + SUBMASTERS   |
| Release a single Submaster | CLEAR + <flash button>   |

## Macros

|                             |   |
|-----------------------------|---|
| Create Auto Macros          | SETUP / PATCH / AUTO MENUS / CREATE AUTO MACROS                     |
| Lamp On Macro               | FIXTURES / <select on MFKs> / MACROS / LAMP ON (fixture dependant)  |
| Lamp Off Macro              | FIXTURES / <select on MFKs> / MACROS / LAMP OFF (fixture dependant) |
| Reset Macro                 | FIXTURES / <select on MFKs> / MACROS / RESET (fixture dependant)    |
| Record a Macro              | MACROS / <hold MFK> / <macro commands> / MACRO                      |
| Play a Macro                | MACROS / <select on MFKs>   |
| Link a Macro to a Memory    | SETUP + MEMORIES / MACROS / <User Macro number> ENTER               |
| Link a Macro to a Submaster | SETUP + SUBMASTERS / MACROS / <User Macro number> ENTER             |